

Kitset – (Add-Edit)

This article describes how to Add or Edit a Kitset. There are two types of Kitsets; Master Kitsets (Code displays “whole numbers”) and Installer Kitsets (Code displays “point numbers”).

NOTE: Master Kitsets cannot be edited directly, they must be Cloned then Edited. On saving they will take on a “point number” and become an Installer Kitset


NOTE: If you have been using SystemFox, the Inhouse Codes have changed. See KAT-1103 for a list of revised Inhouse Codes

To Add a new Kitset;

Adding a new Kitset is done from the KITSETS Tab Library

Quick Flow;

KITSETS Tab > **[Add]** > **Code*** > **Name*** > **Description** > **Icon** > **Heading** > **Products** > **[Save to Library]**

1. Press the **KITSETS** Tab to display the KITSETS Library, then Press the **[Add]** button  to display the KITSET: NEW Window



2. From the KITSET: NEW Window's Kitset Information Section, Enter a **Code***, on Pressing away from the Code field the Kitset's “point number” will display

KITSETS - KITSET: NEW	
Code*	
Description*	
Heading	SWITCH WIRING & INSTALLATION
Use Brand Options	<input checked="" type="checkbox"/>
Name*	
Icon	NOTHING SELECTED


3. From the KITSET: NEW Window's Kitset Information Section, Enter a Kitset **Name*** and **Description***, then from the **Icon** dropdown menu, Select an Icon that goes with the Kitset being made, then select a **Heading** for the Kitset to position under

KITSETS - KITSET: NEW	
Code*	
Description*	
Heading	SWITCH WIRING & INSTALLATION
Use Brand Options	<input checked="" type="checkbox"/>
Name*	
Icon	NOTHING SELECTED


NOTE: If no Icon is selected, the Kitset will not display in the Visbuild Kitset Library, and will only be available to use in Manually entered Quote Sections by keying in the Kitset Code

NOTE: If the Heading selected uses Brands, the “Use Brands Options” displays and a product **MUST** be entered in to each Kitset Brand section


- From the Kitsets COMMON Section enter the Kitset **Products**, by entering Product Codes in the Product Code search field, then entering a QTY for the product




NOTE: If the Kitset Heading selected does not use Brands, all items are entered in to the COMMON Section. If the Kitset Heading selected uses Brands, then common items like; Labour, Travel, Flush Boxes, Cable etc are entered in to the COMMON Section, and additional/branded items like; Additional Labour, Switches, Outlets etc are entered into their BRAND Sections

- Press the **[Save to Library]** button  to save the new Kitset

To Edit a Master Kitset (From the KITSET Tab OR Quote);

- From an open Master Kitset, Press on the **[Clone]** button  to clone the Kitset




- From the cloned Kitset’s Information Section, edit the information as required
- From the cloned Kitset’s COMMON OR BRANDED Sections, Delete product line(s) by Pressing on the delete button at the end of the Product Line OR Add Product by entering a Product Code in the Product Code search field, then entering a QTY for the product


PRODUCT	QUANTITY	UNIT PRICE	TOTAL PRICE	UNIT PRICE	QUANTITY	TOTAL PRICE	UNIT PRICE	QUANTITY	TOTAL PRICE
10540020	1.0mm 2CE TPS 100m	\$0.62	\$1.15	5.00	\$3.10	\$5.50	\$16.07	\$28.90	




- When editing complete, Press the **[Save to Library]** button  to save the editing


NOTE: To access a Kitset from a Quote, Press on the Kitset’s **[OPTIONS]** button , then select option **[Show Kitset Detail]**, then follow steps 1 to 3 above

To Edit an Installer Kitset (From the KITSET Tab OR Quote);

1. From an open Installer Kitset, Press on the [Edit] button  to Edit the Kitset





2. From the Kitset's Information Section, edit the information as required
3. From the Kitset's COMMON OR BRANDED Sections, Delete product line(s) by Pressing on the delete button at the end of the Product Line OR Add Product by entering a Product Code in the Product Code search field




4. When editing complete, Press the [Save to Library] button  to save the editing

To Edit a Master OR Installer Kitset (from a Quote Visbuild Plan);

NOTE: Editing a Kitset from a Quote Visbuild Plan converts it to a Misc Works and saves it to that Quote only. It does not save the Kitset back to the Kitset Library

1. Double Press on the Kitset Icon to display the Kitset Detail Window, then from the Kitset Detail Window, Press on the [Convert to Misc Works] button  (you will be asked if you want to convert the Kitset to a Misc Works, Press the Convert button  to continue and convert)



2. From the Kitset's COMMON OR BRANDED Sections, Delete product line(s) by Pressing on the delete button at the end of the Product Line OR Add Product by entering a Product Code in the Product Code search field

NOTE: You can add any clarification text to the Kitset Name, this will display on the Quote PDF Legend, ALSO a text box and arrow(s) can be used on the Plan to point to and highlight that the Kitset has been modified

3. When editing complete, Press the [Save] button  to save the editing

